

**WHAT IS CLAIMED IS:**

1. An apparatus for detecting a data transmission rate transmitted through a serial bus, the apparatus comprising:

a data transmission rate detecting unit for detecting a data transmission rate of bit stream data transmitted through a predetermined transmission line;

5 a sampler for sampling a data transmission rate detected by the data transmission rate detecting unit at a predetermined period;

a low-pass filter for low-pass filtering a value sampled by the sampler to produce a low-pass filtered value;

10 an error detecting unit for detecting an error value in the data transmission rate of the transmitted bit stream data using the value sampled by the sampler and the low-pass filtered value;

a comparing unit for comparing the error value detected by the error detecting unit with a reference error level; and

15 an estimated data transmission rate output unit for outputting an estimated data transmission rate based on the low-pass filtered value when the error value is smaller than the reference error level.

2. The apparatus for detecting a data transmission rate according to claim 1, wherein the error detecting unit is formed to detect an error value of one isochronous period, the comparing unit is formed to compare the error value of the one isochronous period with the reference error level, and the

5 estimated data transmission rate output unit is formed to output the estimated data transmission rate of the one isochronous period, in a case where the serial bus is an IEEE 1394 bus.

3. The apparatus for detecting a data transmission rate according to claim 2, wherein the error detecting unit is formed to calculate a low-pass filtered value of the one isochronous period from the low-pass filtered value, to calculate a sampled value of the one isochronous period from the sampled  
5 value, to divide an absolute difference between the low-pass filtered value of the one isochronous period and the sampled value of the one isochronous period by the low-pass filtered value of the one isochronous period, and to detect an error of the one isochronous period.

4. The apparatus for detecting a data transmission rate according to claim 2, wherein the comparing unit sets one error level selected from a plurality of error levels by a user as the reference error level.

5. The apparatus for detecting a data transmission rate according to claim 2, wherein the error detecting unit is formed to calculate a low-pass filtered value of the one isochronous period from the low-pass filtered value, to calculate a sampled value of the one isochronous period from the sampled  
5 value, to divide an absolute difference between the low-pass filtered value of the one isochronous period and the sampled value of the one isochronous period by the low-pass filtered value of the one isochronous period, and to detect an error value of the one isochronous period; and

wherein the comparing unit sets a value obtained when one error level  
10 selected by a user from a plurality of error levels is multiplied by the sampled  
value of the one isochronous period, as the reference error level, and is formed  
to compare the error value of the one isochronous period with the reference  
error level.

6. The apparatus for detecting a data transmission rate according  
to claim 2, wherein the estimated data transmission rate output unit calculates  
a low-pass filtered value of the one isochronous period from the low-pass  
filtered value and outputs the low-pass filtered value of the one isochronous  
5 period as the estimated data transmission rate.

7. The apparatus for detecting a data transmission rate according  
to claim 2, wherein the low-pass filter is an infinite impulse response (IIR)  
low-pass filter.

8. The apparatus for detecting a data transmission rate according  
to claim 1, wherein the predetermined transmission line is a line between an  
external input/output interface unit for interfacing with an MPEG transport  
stream (TS) demultiplexer and an audio/video interface unit.

9. The apparatus for detecting a data transmission rate according  
to claim 1, wherein the apparatus detects the data transmission rate in a word  
unit, and a predetermined sampling frequency is set to 125Hz.

10. An apparatus for detecting a data transmission rate through a serial bus after a bandwidth for the serial bus is allocated to a system, the apparatus comprising:

a data transmission rate detecting unit for detecting a data transmission  
5 rate of bit stream data transmitted through a predetermined transmission line;

a sampler for sampling a data transmission rate detected by the data  
transmission rate detecting unit at a predetermined period;

a low-pass filter for low-pass filtering a value sampled by the sampler;

an error detecting unit for detecting an error value in the data  
10 transmission rate of the transmitted bit stream data using the value sampled by  
the sampler and a low-pass filtered value;

a first comparing unit for comparing the error value detected by the  
error detecting unit with a reference error level;

an estimated data transmission rate output unit for outputting an  
15 estimated data transmission rate based on the low-pass filtered value when the  
error value is smaller than the reference error level; and

a second comparing unit for comparing the estimated data transmission  
rate with an upper bound and a lower bound to notify whether the estimated  
data transmission rate output from the estimated data transmission rate output  
20 unit exists between the upper bound and the lower bound set by a user

according to the allocated bandwidth and to determine whether the estimated data transmission rate is output.

11. The apparatus for detecting a data transmission rate according to claim 10, wherein the second comparing unit generates an interrupt for notifying whether the estimated data transmission rate output from the estimated data transmission rate output unit exists between the upper bound  
5 and the lower bound and an output control signal to the estimated data transmission rate output unit so as to output the estimated data transmission rate, in a case where the estimated data transmission rate does not exist between the upper bound and the lower bound.

12. The apparatus for detecting a data transmission rate according to claim 10, wherein the error detecting unit is formed to detect an error value of one isochronous period, the first comparing unit is formed to compare the error value of the one isochronous period with the reference error level, and  
5 the estimated data transmission rate output unit is formed to output an estimated data transmission rate of the one isochronous period, in a case where the serial bus is an IEEE 1394 bus.

13. The apparatus for detecting a data transmission rate according to claim 10, wherein the predetermined transmission line is a line between an external input/output interface unit for interfacing with an MPEG transport stream (TS) demultiplexer and an audio/video interface unit.

14. A method for detecting a data transmission rate through a serial bus, the method comprising the steps of:

(a) detecting a data transmission rate of bit stream data transmitted through a predetermined transmission line;

5 (b) detecting an error in the data transmission rate at a first predetermined period using the detected data transmission rate;

(c) comparing the error with a reference error level;

(d) checking present operation mode when the error is smaller than the reference error level;

10 (e) outputting an estimated data transmission rate for the first predetermined period using the data transmission rate when the present operation mode is a transmit/receive average mode; and

(f) outputting the estimated data transmission rate for the first predetermined period in a case where the estimated data transmission rate for  
15 the first predetermined period does not exist between a predetermined upper bound and a predetermined lower bound when the present operation mode is a transmit/receive tracking mode.

15. The method for detecting a data transmission rate according to claim 14, wherein the step (b) comprises the steps of:

(b1) sampling the detected data transmission rate at a first predetermined frequency;

5 (b2) filtering a sampled value in the step (b1) by using low-pass filtering; and

(b3) detecting the error in the data transmission rate of the bit stream data using the sampled value and a low-pass filtered value in the step (b2).

16. The method for detecting a data transmission rate according to claim 15, wherein the reference error level in the step (c) is one error level selected from a plurality of error levels by a user, or a value resulting from performing a predetermined operation on the one error level and the sampled  
5 value.

17. The method for detecting a data transmission rate according to claim 15, wherein the step(a) is performed in a word unit, the first predetermined period is one isochronous period, and the first predetermined frequency is 125Hz, in a case where the serial bus is an IEEE 1394 bus.

18. The method for detecting a data transmission rate according to claim 15, wherein the low-pass filtered value of the first predetermined period detected using the low-pass filtered value in the step (b2) is output as the estimated data transmission rate in the steps (e) and (f).

19. The method for detecting a data transmission rate according to claim 14, wherein the predetermined upper bound and the predetermined lower bound in the step (f) are determined on the basis of the estimated data transmission rate output in the step (e), and the step (f) comprises the step of

- 5 notifying whether the estimated data transmission rate exists between the predetermined upper bound and the predetermined lower bound.

2019-09-10 14:00:00